


ELECTRIC FIRING UNIT - GPMG
MG223A (AEI-12138)
23.5-28V D.C.
COIL RESISTANCE 5.17 Ω
40 SECONDS (MAX) RATING
NSN 1005-99-964-2620

GPMG E F U L1A1

NSN 1005-99-964-2620

AEI SYSTEMS



ELECTRICAL FIRING UNIT L1A1

L20A2 & L44A1 General Purpose Machine Gun (GPMG) 7.62 mm

MOUNTING

- As per standard trigger mechanism; Quick release pins not supplied.

POWER SUPPLY

- Power input; 23.5 to 28 VDC
- Solenoid coil resistance; 5.17 ohms
- Power duration; 40 seconds max.
- Connection; 10SL-3P

IDENTIFICATION

- ELECTRICAL FIRING UNIT L1A1
- NSN 1005-99-964-2620
- AEI Part No. AEI-12138
- Alt Part No. MC223A



QUALITY ASSURANCE / OBSOLESCENCE MANAGEMENT

Each Electrical Firing Unit L1A1 manufactured by AEI Systems is hand built and mechanically and electrically function tested. Customers are encouraged to witness acceptance testing prior to dispatch for total 'peace of mind'.

Obsolescence management guarantees total supportability of all Electrical Firing Unit's supplied by AEI Systems now and long into the future.



ELECTRICAL FIRING UNIT L1A1

L20A2 & L44A1 General Purpose Machine Gun (GPMG) 7.62 mm

DESCRIPTION

Where a remote firing GPMG is an operational requirement for land or naval weapon mount installations, the Electrical Firing Unit L1A1 and Recoil Buffer Mk.2 are required.

The Electrical Firing Unit L1A1 incorporates the trigger mechanism safe/fire catch and electrical solenoid in the assembly.

The trigger mechanism housing consists of a deeply recessed rectangular block that accommodates the trigger group components and is closed by a cover plate. Axis pins, protruding through the housing and cover plate, are secured in place each side by flat spring retainer clips.

The lower part of the housing is bored longitudinally to receive the solenoid rod. At the rear, the housing has a formed flange to receive the solenoid housing which is secured in place by four bolts and stiff nuts. An electrical socket assembly, on the rear lower side, provides the firing circuit connection. The solenoid operates between 23.5 and 28 V DC and has a rating of 40 seconds. Solenoid operation in excess of 40 seconds will damage the unit.



FUNCTION

The action of the Electrical Firing Unit L1A1 trigger mechanism is identical with that of the standard GPMG weapon, but the trigger movement is initiated by movement of the solenoid.

When the solenoid is energised by remote fire command the plunger and rod, bearing against the trigger projection, rotates the trigger and effects sear release. When remote fire command ceases, the plunger and rod are returned by action of the compressed plunger return spring.

WWW.AEI-SYSTEMS.COM